AMENDMENTS TO THE CLAIMS:

This listing of claims will replace all prior versions, and listings, of claims in the application.

LISTING OF CLAIMS:

1. (Canceled)

2. (Previously presented)   The method according to claim 4, further comprising: wherein the memory comprises a read-only memory (ROM).

3. (Previously presented)   The method according to claim 4 wherein, for serially generating the Gold code sequence, the method further comprising:

adding the fixed integer value n and the count value i for each count value i of the plurality of count values.

4. (Currently amended)   A method for use in generating one or more data sequences for spread spectrum communications, the method comprising:

serially generating a Gold code sequence by, for each count value i of a plurality of count values:

retrieving from memory a bit of a pseudorandom noise (PN) sequence corresponding to an (i+n)th position in the PN sequence, where n is a fixed integer value;

retrieving from memory a bit of the PN sequence corresponding to an (q*i)th position in the PN sequence, where q~~i~~ is a fixed integer value;

adding the bit~~d~~ corresponding to the (i+n)th position with the bit corresponding to the (q∗i)th position; and

wherein, for serially generating the Gold code sequence, the method further comprises[[:]] multiplying q and the count value i for each count value i of the plurality of count values.

5. (Currently amended)   A method for use in generating one or more data sequences for spread spectrum communications, the method comprising:

serially generating a Gold code sequence by, for each count value i of a plurality of count values:

retrieving from memory a bit of a pseudorandom noise (PN) sequence corresponding to an (i+n)th position in the PN sequence, where n is a fixed integer value;

retrieving from memory a bit of the PN sequence corresponding to an (q∗i)th position in the PN sequence, where q~~i~~ is a fixed integer value;

adding the bit~~d~~ corresponding to the (i+n)th position with the bit corresponding to the (q∗i)th position; and

wherein retrieving from memory a bit of the PN sequence corresponding to the (i+n)th position comprises applying an (i+n) value to the address inputs of the memory; and

wherein retrieving from memory a bit of the PN sequence corresponding to the (q∗i)th position comprises applying an (q∗i) value to the address inputs of the memory.

6. (Currently amended)   A method for use in generating one or more data sequences for spread spectrum communications, the method comprising:

serially generating a Gold code sequence by, for each count value i of a plurality of count values:

retrieving from memory a bit of a pseudorandom noise (PN) sequence corresponding to an (i+n)th position in the PN sequence, where n is a fixed integer value;

retrieving from memory a bit of the PN sequence corresponding to an (q∗i)th position in the PN sequence, where q¹ is a fixed integer value;

adding the bit̶d̶ corresponding to the (i+n)th position with the bit corresponding to the (q∗i)th position; and

wherein the Gold code sequence is a first Gold code sequence, the method further comprising[[:]] serially generating a second Gold code sequence by, for each count value i of the plurality of count values;[[:]]

retrieving from memory a bit of the PN sequence corresponding to the (i+n+m)th position in the PN sequence, where "m" is a fixed integer value;

retrieving from memory a bit of the PN sequence corresponding to the (q∗i + q∗m)th position in the PN sequence; and

adding the bit corresponding to the (i+n+m)th position with the bit corresponding to the (q∗i + q∗m)th position.

7. (Cancelled)

8. (Cancelled)

9. (Previously presented)   In a dual mode Code Division Multiple Access (CDMA), a method for generating an nth Gold code from a pseudorandom noise (PN) sequence stored sequentially in a memory as x(0), x(1), ..., the method comprising the steps of:

accessing the memory sequentially starting from location n in order to generate the sequence x(i+n), where n is a fixed integer value;

accessing the memory non-sequentially starting from a first location (k) and then accessing each qth location in order to generate the sequence x(q∗i+ k) where q is a fixed integer value; and

adding on a bit-by-bit basis the resulting two retrieved sequences x(i+n) and x(q∗i +k).

10. (Currently amended) A method of generating a complex Gold Code sequence, Z2n(i), ~~applicable to the Universal Mobile Telephone Service (UMTS) standard,~~ where, x is a PN sequence stored sequentially as x(0), x(1), ... in a memory, the PN sequence having a length equal to 2M-1, the method comprising the steps of:

accessing from the memory in sequences of x(i+n+m), x(q*i + q*m), x(i+n) and x(q*i);

and

performing the equation:
$$Z2n(i) = x(i + n) + x(q*i) + j[x(i + n + m) + x(q*i + q*m)]$$
where, [["]]n[["]] and [["]]q[["]] are fixed integer values to produce the complex Gold Code sequence, and [["]]M[["]], [["]]n[["]] and [["]]i[["]] are integer values.

11. (Previously presented) A data sequence generator for serially generating one or more data sequences, the data sequence generator comprising:

a memory;

data stored in said memory;

the data comprising a pseudo-random noise (PN) sequence;

a counting device;

a first adder, including:

a first input coupled to an output of the counting device;

a second input which receives a value n, wherein n is an integer value;

a multiplier, including:

a first input coupled to the output of the counting device;

a second input which receives a value q, wherein q is an integer value;

a first multiplexer, including:

a first input coupled to an output of the first adder;

a second input coupled to an output of the multiplier; and

an output for coupling to memory address inputs of the memory.

12. (Currently amended) The data sequence generator according to claim 11, ~~further comprising:~~ wherein the memory compris~~ing~~es a read-only memory (ROM).

13. (Original) The data sequence generator according to claim 11, further comprising:

an output of the memory to provide serially-generated PN sequences responsive to the counting device.

14. (Original) The data sequence generator according to claim 11, further comprising:

a first latch having an input coupled to an output of the memory;

a second latch having an input coupled to the output of the memory;

a second adder, including:

a first input coupled to an output of the first latch;

a second input coupled to an output of the second latch; and

an output to provide a serially-generated Gold code sequence.

15. (Previously presented) The data sequence generator according to claim 11, further comprising:

a second multiplexer, including:

a first input coupled to the output of the first multiplexer;

a second input coupled to the output of the counting device; and

an output coupled to an address input of the memory.

16. (Previously presented)   The data sequence generator according to claim 11, further comprising:

a first latch having an input coupled to an output of the memory;

a second latch having an input coupled to the output of the memory;

a second adder, including:

a first input coupled to an output of the first latch;

a second input coupled to an output of the second latch;

an output to provide a serially-generated Gold code sequence;

a second multiplexer, including:

a first input coupled to the output of the second adder;

a second input coupled to the output of the memory; and

an output to provide, in a time-multiplexed fashion the serially-generated PN sequence and the serially-generated Gold code sequence.

17. (Previously presented)   The data sequence generator according to claim 11, further comprising:

a second multiplexer, including:

a first input coupled to the output of the first multiplexer;

a second input coupled to the output of the counting device;

an output coupled to an address input of the memory;

a first latch having an input coupled to an output of the memory;

a second latch having an input coupled to the output of the memory;

a second adder, including:

a first input coupled to an output of the first latch;

a second input coupled to an output of the second latch;

an output to provide a serially-generated Gold code sequence;

a third multiplexer, including:

a first input coupled to the output of the second adder;

a second input coupled to the output of the memory; and

an output to provide, in a time-multiplexed fashion, a serially-generated PN sequence and a serially-generated Gold code sequence.

18. (Currently amended) A data sequence generator, comprising:

a read-only memory (ROM) storing a pseudo-random noise (PN) sequence;

a counter;

a first adder, including:

a first input coupled to the output of the counter;

a second input which receives a value n, wherein n is an integer;

a multiplier, including:

a first input coupled to the output of the counter;

a second input which receives a value q, wherein q is an integer;

a first multiplexer, including:

a first input coupled to an output of the first adder;

a second input coupled to an output of the multiplier;

a second multiplexer, including:

a first input coupled to an output of the first multiplexer;

a second input coupled to the output of the counter; and

an output of the second multiplexer coupled to an address input of the ROM.

19. (Original) The data sequence generator according to claim 18, further comprising:

a first latch coupled to an output of the ROM;

a second latch coupled to the output of the ROM;

a second adder, including:

a first input coupled to an output of the first latch;

a second input coupled to an output of the second latch; and

an output to provide a Gold Code sequence.

20. (Original)   The data sequence generator according to claim 18, further comprising:

a first latch coupled to an output of the ROM;

a second latch coupled to the output of the ROM;

a second adder, including:

a first input coupled to an output of the first latch;

a second input coupled to an output of the second latch;

a third multiplexer, including:

a first input coupled to the output of the ROM;

a second input coupled to an output of the second adder; and

an output to selectively provide the PN sequence and a Gold Code sequence.

21. (Previously presented)   The data sequence generator according to claim 20, wherein the ROM comprises a first ROM and a second ROM and the output of the second multiplexer is coupled to memory address inputs of both the first and the second ROM;

a first PN sequence is stored in the first ROM and a second PN sequence is stored in the second ROM;

the first and second latches are coupled to the output of the first ROM; and

the first input of the third multiplexer is coupled to the output of the second ROM.

22. (Currently amended)   A data sequence generator for use in direct sequence spread spectrum (DSSS) communications, comprising:

memory;

a pseudo-random noise (PN) sequence stored in the memory;

a counter for use in generating each count value i of a plurality of count values;

an output of the memory to provide, for each count value i[[I]] received at memory address inputs, a bit of the PN sequence corresponding to the (i)th position in the PN sequence, where n is a fixed integer value;

an output of the memory to provide, for each (i+n) value received at the memory address inputs, a bit of the PN sequence corresponding to the (i+n)th position in the PN sequence, where q is a fixed integer value;

an output of the memory to provide, for each (q*i) value received at the memory address inputs, a bit of the PN sequence corresponding to the (q*i)th position in the PN sequence; and

an adder to provide a sum of the bit corresponding to the (i+n)th position and the bit corresponding to the (q*i)th position, to thereby provide a Gold code sequence.